

T1DP 0v High Voltage Desk Top Power Supply

Operators Manual

Contents:

1. General information
2. Technical Data
3. Front panel
4. Operation
5. Polarity setting
6. Control via computer interface

WARNING!

- It is not allowed to use the unit if the covers have been removed.
- It is not allowed to connect or disconnect the HV cable if HV is ON !
- We decline all responsibility for damages and injuries caused by an improper use of the module. It is highly recommended to read the operators manual before any kind of operation.

Note

The information in this manual is subject to change without notice. We take no responsibility for any error in the document. We reserve the right to make changes in the product design without reservation and without notification to the users.

Filename T1DP0x_HW_FAST_eng.____; Version 2.02 as of 09-12-16

1. General information

The model T1DP 0v is a high voltage desk top supply which offer a very stable output voltage up to 6 kV for use in industry and research. The output is generated by means of a high voltage module of the DPS-series, which is supplied by means of an AC/DC converter.

Main Characteristics:

- High voltage desk top power supplies with either front-panel or remote control
- Output voltages with very low ripple and noise
- Compact and ruggedized enclosure
- Polarity fixed ex works or switchable electronically with **option EPU**
- Output short circuit and overload protected

2. Technical Data

1 channel HV-PS	T1DP	005	01	02	03	04	05	06
Output voltage V_{Onom}		500 V	1 kV	2 kV	3 kV	4 kV	5 kV	6 kV
Output current I_{Onom}		10 mA	10 mA	6 mA	4 mA	3 mA	2 mA	1,5 mA
Polarity		positive or negative ex works or switchable electronically at $V_{OUT} = 0$!						
Ripple & noise		typ. < 2 mV _{P-P} , max. 7 mV _{P-P}						
Stability:	$\frac{\Delta V_O}{\Delta V_{INPUT}}$	< $1 * 10^{-5}$						
	ΔV_O (no load to full load)	< $5 * 10^{-5}$						
Temperature coefficient		< $5 * 10^{-5}/K$						
Voltage measurement	Resolution:	$V_{Onom} < 1$ kV: 0,1 V ; $V_{Onom} \geq 1$ kV: 1 V / 4-digit LCD display						
	Accuracy:	$\pm (1\% * V_{Onom})$ (for one year)						
Voltage setting	manual:	via 10-turn potentiometer ("LOC")						
	REMOTE:	via analog I/Omit $V_{SET/MON} = 0$ bis 5 V ("REM") oder interface						
Current measurement	Resolution:	$I_{Onom} \geq 10$ mA: 10 μ A ; $I_{Onom} < 10$ mA: 1 μ A / 4-digit LCD display						
	Accuracy:	$\pm (1\% * I_{Onom})$ (for one year)						
Current setting	manual:	via 10-turn potentiometer ("LOC")						
	REMOTE:	via analogue I/O with $V_{SET/MON} = 0$ to 5 V ("REM") or interface						
Rate of change of V_O		fixed: $V_{Onom} / 4s$ (at HV-ON/OFF)						
Protection		Output short circuit and overload protected. Attention ! There is only one short circuit or arc per second allowed! The integral output current must limited to the max. output current of the module external otherwise.						
Remote control		via analog I/O ("REM"), RS232 ("RS232") or USB ("USB") interface						
Line voltage AC (V_{INPUT})		100 to 240 V-AC; 50/60 Hz; fused with 2 A-slow						

One channel HV-PS		T1DP 0v
Connectors	HV output: analogue I/O:	SHV-Connector 9-pin male D-Sub connector
Desk case	Size (W/H/D) : (310/90/280, 310 with SHV) mm; Weight: ca. 2,7 kg	
Operating temperature	0 ... +50 °C	
Storage temperature	-20 ... +60 °C	
9-pin male D-Sub connector "analog I/O" on the rear side		
PIN	Name	Description
1	n.c.	
2	V_I _{MON}	Monitor voltage corresponding I _O : I _O = 0 to I _{Onom} ⇒ V ₂₋₆ = 0 to 5 V (R _i = 10 kΩ)
3	INH	INHIBIT (TTL level, LOW ⇒ V _O = 0, [LOW to] HIGH or open ⇒ V _O = V _{SET} with ramp)
4	V_I _{SET}	Setting current (R _{IN} = 10 kΩ): V ₄₋₆ = 0 to 5 V ⇒ I _O = 0 to I _{Onom} ± 1% n.c. ⇒ I _{Onom} is possible
5	V_Pol	Setting polarity only with option EPU : (TTL level, LOW ⇒ negative, HIGH ⇒ positive)
6	GND	GND = V _{SET_0V} Signal 0 V (connected to the metal module box)
7	V_V _{MON}	Monitor voltage corresponding V _O : V _O = 0 to V _{Onom} ⇒ V ₇₋₆ = 0 to 5 V (R _{OUT} = 10 kΩ)
8	V_V _{SET}	Setting voltage: V ₈₋₆ = 0 to 5 V (R _{IN} ≈ 300kΩ) ⇒ V _O = 0 to V _{Onom} ± 1%
9	V _{REF}	V ₉₋₆ = 5 V (1 mA) Reference voltage for a external potentiometer (Sliding contact on V_V _{SET} and/or V_I _{SET})

3. Front panel

